

# IFC 200/202 Data Logger Interface QUICK INSTALLATION GUIDE

For Windows XP SP3 or later

### **IMPORTANT:** Do not connect the IFC to your PC until instructed to do so.

The IFC interface cable packages allow for the communication between stand alone data loggers and the MadgeTech 4 Software. Directly connect the IFC to a PC to start and stop the data logger or to download readings.

### Launch the MadgeTech 4 Installer

MadgeTech 4 Standard Software can be downloaded from the MadgeTech website (**madgetech.com/software**). See the MadgeTech 4 Software Manual for complete installation instructions.

- 1. Open the **MT4 folder** from the newly downloaded file and double click the **MTInstaller.exe** file to launch the Setup Wizard.
- 2. Select the Installer Language and click **OK**.
- 3. Accept the End-User License Agreement and click Next.
- 4. Choose the installation options and click Next.
- 5. MadgeTech 4 is now ready to install. Click **Install** to begin the installation.
- 6. Click Finish when the installation is complete.

The MadgeTech 4 Software requires the .NET Framework 4.0 to be installed on the PC. The Windows 8 and Windows 10 operating system comes with a newer version of the .NET Framework already installed. If the .NET Framework 4.0 has not been installed on the PC, download it from the Microsoft.com website.

After the .NET Framework 4.0 installation has been confirmed, install the MadgeTech 4 Software following the steps above.

## Connecting the IFC to MadgeTech 4 Software

- 1. Connect the USB end of the IFC200/202 into a USB port on the PC.
- 2. Once the IFC200/202 is plugged in, a New Hardware Found message will appear on the PC. The new drivers will automatically configure for use with the Interface cable. A message will then appear that the new hardware is installed and ready to use.
- Verify the IFC has been installed correctly by launching the MadgeTech 4 Software and navigating to File > Options > Communication. You should see the IFC you installed listed on this screen.



Welcome to the MadgeTech	4 Setup Wi	zard	$\propto$
The Setup Wizard will install MadgeTech 4 c the Setup Wizard.	on your computer.	Click Next to contir	ue or Cancel to
	Back	Next	Cancel

Install Options	
Add desktop shortcut	
Add Start menu shortcuts	
Enable crash reporting	
Automatically submit usage informati	ion to help improve the software
Transmission is secure and anonymous. information is transmitted.	No personally identifiable or data logger recorded
	Back Next Ca
Change which interfaces are used to search for de	
Interface selection	
Interface selection Search for devices using serial interfaces Search for devices using USB interfaces Detected interfaces	
Interface selection  Search for devices using senal interfaces  Search for devices using USB interfaces	
Interface selection Search for devices using serial interfaces Search for devices using USB interfaces Detected interfaces	

OK Cancel

Device Display File Reports Alarmo Units Address Email se Commu Reports Wireless Interop Cloud

About



# Testing the Data Logger and Interface Connection

- 1. To verify that the Interface drivers are installed properly, start the MadgeTech 4 Software. (If necessary, see the software manual for additional instructions on the software.)
- 2. When the IFC200/202 is connected to the PC, the blue LED indicator should be lit, if the drivers are properly installed and the interface is detected by Windows. If the indicator light is not on, unplug the interface cable and verify that the USB drivers have been installed. Wait 5 seconds and plug it back into the PC.
- 3. Plug the IFC200/202 cable into the data logger.
- 4. Your device will appear in the Connected Devices panel.

22 <b>]</b>							MadgeTech 4									ē	23
File Device Report																^	Help
Custom Batch Start	mload Rese	et Workflows E		Disable Cloud Monitoring		Download	Manage Alarm Rules Log Alarms		es Engineering Units		Release Wireless						
File Database 👻 📮	Connected	1 devices															
Datasets	Search		P Search	h by: No pre	ference		• 🔲 On	ly show cla	imed wireless o	levices						Refres	h
🕤 Deleted Datasets	Cloud	Device ID	Mod		Serial No.		Status		Progress	Re	adings	Re	ading Interval		Time Zo		S
Example Datasets		MultiChannel	RHTem	ip101A	R70987		Stopped				0		15 seconds	8/2/2021 9:56:15 AM ED	T	EDT	-
A 🛃 Reports																	
👕 Deleted Reports																	l
	•						III								_		•
	Connected devices Files																

#### Additional Information

For additional information or troubleshooting assistance, visit us online at **madgetech.com**, contact us at **support@madgetech.com** or call (603) 456-2011.